

BRYSTON  
**21B<sup>3</sup>**

## THREE-CHANNEL AMPLIFIER

Bryston's 21B<sup>3</sup> amplifier was crafted to provide superb amplification to your active speaker system. Paired together, two of these amps will drive your active system with breathtaking ease and clarity!

The 21B<sup>3</sup> three channel amplifier is convection cooled which means there are no fans or moving parts to break. The 21B<sup>3</sup> is housed in a fully aluminum chassis with your choice of silver or black front faceplate.

Available now from The Sound Organization for \$11,995.



### The 21B<sup>3</sup> Amplifier features

- Inputs: 3x Balanced Inputs (XLR or TRS), 3x Single Ended Inputs (RCA)
- Selectable gain at 23 or 29dB
- Harmonic Distortion (1st Channel):  $\leq .005\%$  from 20Hz to 20kHz at 600W
- Noise below full output (1st Channel): -113dB single ended, -116dB balanced
- Slew Rate:  $>60\text{V}/\mu\text{S}$
- Power Bandwidth:  $<1\text{Hz}$  to  $>100\text{kHz}$
- Damping Factor:  $>300$  at 20Hz (8 $\Omega$ )
- Capabilities: 1x 600W into 8 $\Omega$ , 2x 300W into 8 $\Omega$ , 1x 900W into 4 $\Omega$ , 2x 500W into 4 $\Omega$

